

146.740 REPEATER AUDIO ADJUSTMENTS

WITH HANDHELD RADIO

SEND TOUCH TONE #3 ON 146.140MHZ

ADJUST CAT300 RX R17 POT FOR 200 MV

AT TP 4

WHEN LINK ICOM RADIO IS RECEIVING A #3

TOUCH TONE ON 444.775mhz ADJUST ICOM

TRANSMITTING LEVEL OUT POT FOR 200mv

AT TP4

USING SERVICE MONITOR SET TO 146.740mhz

ADJUST R5 FOR 3KC DEVIATION WHEN

REPEATER IS RECEIVING 146.140 #3 TOUCH

TONE FROM HAND HELD RADIO.

SET SERVICE MONITOR FOR 444.775mhz

ADJUST "IN" POT ON ICOM UHF RADIO FOR

3KC DEVIATION ON 444.775 MHZ

WITH

#3 TOUCH TONE TRANSMITTED ON 146.140mhz

HANDHELD RADIO